

美國規格 NEMA 插座系列

GREEN E²

110~120 AC 交流電圖

15 安培

典型插座

NEMA 5-15



NEMA L5-15



舊型插座

NEMA 1-15



20 安培

NEMA 5-20



NEMA L5-20



110 / 220 AC 交流電圖



14-20



30 安培

露營/拖車

NEMA TT-30

NEMA 5-30



NEMA L5-30



乾衣機

NEMA 14-30



50 安培

電動車

NEMA 5-50



電動車 / 電烤箱

NEMA 14-50



14-60



220~240 AC 交流電圖

NEMA 6-15



NEMA L6-15



NEMA 6-20



焊工或電漿切割機

NEMA L6-20



NEMA 10-30



NEMA 6-30



焊工或電漿切割機

NEMA L6-30



NEMA 10-50



NEMA 6-50

電動車

NEMA L6-50



電腦插座

IEC-60320-C13



IEC-60320-C19




三相插座

NEMA L15-30



NEMA L21-30

圖示說明



- 1 圖示均為母插座 Receptacle
- 2 圖示比例及腳位小於實際尺寸
- 3 公插頭 Plug 為圖示之鏡像

★ 安全注意：

電動車為高功率、高安培用電，插頭/插座皆為”損耗材料”，每次使用需檢查插頭及插座。如發現週圍出現高溫或塑膠融化現象，為使用不當或金屬片老化，應立即更換插座與插頭，確保用電安全